



These **PATENTED** tools are designed to open fiber jackets and loose buffer tubes to provide easy fiber access. The buffer tube slitting is done without damage to the fiber. Blades are replaceable.

Simple to use:

- Select the correct groove. Grooves marked with the recommended cable size
- Place the cable in the groove to be used
- Note: The arrow on the top of the tool indicates the pulling direction and the line indicates the blade location
- Close the tool making sure lock is engaged and pull to slit the cable

| SPECIFICATIONS | MS-6 | MS-26 |
|--------------------------|--|---|
| DESCRIPTION | Mid Span Slitter (1.2mm-3.3mm) | Mid Span Slitter (2.9mm-6.8mm) |
| NO. OF PRECISION GROOVES | 6 | 5 |
| GROOVE SIZES (MM) | 1.2-1.5, 1.5-1.8, 1.8-2.1, 2.1-2.5, 2.5-2.9, 2.9-3.3 | 2.9-3.6, 3.6-4.4, 4.4-5.2, 5.2-6.0, 6.0-6.8 |
| REPLACEMENT CARTRIDGE | MSB-1533 | MSB-2968 |



Replacement Cartridges

| JONARD P/N | DESCRIPTION |
|------------|------------------------------|
| MS-1533 | Replacement Blades for MS-6 |
| MS-2968 | Replacement Blades for MS-26 |

MADE FOR LIFE®